

METHOD OF FORMING HIGH QUALITY WAVEGUIDES BY VAPOR-PHASE
PROTON-EXCHANGE PROCESS WITH POST-THERMAL ANNEALING AND
REVERSED PROTON-EXCHANGE

FIELD OF THE INVENTION

The present invention relates generally to optical device fabrication and more specifically to methods of fabricating waveguides having engineerable refractive index profiles as well as preferred optical properties such as waveguide propagation loss, nonlinearity, electro-optical (EO), acusto-optical (AO) and uniformity, for example.

BACKGROUND OF THE INVENTION

A vapor phase proton exchange (VPE) process can be used to form a preferred homogeneous crystal phase in several ferroelectric crystals such as lithium niobate (LiNbO_3) and lithium tantalate (LiTaO_3). Important optical properties, such as electro-optical (EO), acusto-optical (AO) and nonlinear optical properties can be preserved by VPE processing as compared to the observed degradation in these properties when other liquid-phase proton exchange processes are used.

The superior optical properties with lower waveguide propagation loss and higher nonlinearity are well suited for several applications. As an example, Figs. 1 (a) - (g) illustrate the crystalline phase of different processes resolved by X-ray rocking curve measurements in the prior art. That is:

(a) APE (Annealed proton-exchange) waveguide: peak shift at 162 second (alpha phase);

(b) PE (proton exchange via liquid phase) waveguide: peak shift 594 second (beta phase);

(c) waveguide of VPE for 8 hours at 300°C: peak shift 504 second (kappa phase);

(d) waveguide of VPE for 10 hours at 300°C: peak shift 504 second (kappa phase);

(e) waveguide of VPE 12 hours at 300°C.: peak shift 504 second (kappa phase);

(f) waveguide of VPE 20 hours at 300°C.: peak shift 504 second (kappa phase); and

(g) waveguide of VPE 30 hours at 300°C.: peak shift 504 second (kappa phase).

The alpha and kappa phase in general exhibit superior optical properties, as compared to beta phase. However, as compared to alpha phase, the kappa phase has a higher index profile, which is preferred in several waveguide applications. Figs. 1 (c) through (g) show the peak shift of 504 second, which reveals the kappa phase of those samples. A kappa structure has shown to exist with a maximum depth below 5μm under the example process condition. For deeper depth, it can also be achieved via careful control of vapor phase process, such as temperature, time, and acid concentration."

However, waveguides formed by conventional VPE processes in general form a step-like index profile with a high refractive index jump as shown in Figs. 2 and 3, respectively. In Figs. 2 and 3:

- (a) APE (annealed proton-exchange) waveguide;
- (b) PE (proton exchange via liquid phase) waveguide for 36 hours duration at 160°C;
- (c) waveguide for VPE for 8 hours duration at 300°C;
- (d) waveguide for VPE for 10 hours duration at 300°C;
- (e) waveguide for VPE for 12 hours duration at 300°C;
- (f) waveguide for VPE for 20 hours duration at 300°C; and

(g) waveguide for VPE for 30 hours duration at 300°C.

As shown in Figs. 2 and 3, the VPE process yields high index profile waveguides (samples c, d, e, f and g) as compared to APE process waveguides (sample a - alpha phase structure with $\Delta n_e < 0.03$). Although PE waveguide (sample b) can have a higher index profile as compared to VPE process waveguide, the sample prepared by PE process in general results in degraded optical properties. Thus VPE processes permits fabrication of tightly confined waveguides which benefits the efficiency in waveguide nonlinear frequency conversion. The kappa (k) phase (samples c to g) can be achieved for different depths as long as the process can be performed at an optimized fabrication condition. This property allows one to design and fabricate VPE waveguides for a variety of applications.

However, such single step VPE process waveguides of Figs. 2 and 3 can not necessarily generate optimized designs for applications.

The J. Rams et al. article entitled "Nonlinear optical efficient LiNbO₃ waveguides proton exchanged in benzoic acid vapor: Effect of the vapor pressure," Journal of Applied Physics, Vol. 85, No. 3, p.p. 1322 to 1328 (1 February 1999) describes the effect of the vapor pressure on the properties of LiNbO₃ waveguides proton-exchanged in benzoic acid vapor.

The J. Rams et al. article entitled "Preparation of proton-exchange LiNbO₃ waveguides in benzoic acid vapor," J. Opt. Soc. Am. B, Vol. 16, No. 3, p.p.

401 to 406 (March 1999) describes formation of alpha- or beta-phase LiNbO_3 waveguides by proton-exchange of x- and z-cut substrates in benzoic acid vapor.

The M. L. Bortz et al. article entitled "Depth profiling of the d_{33} nonlinear coefficient in annealed proton exchanged LiNbO_3 waveguides," Appl. Phys. Lett., Vol. 62, No. 17, p.p. 2012 to 2014 (26 April 1993) describes depth profiling of the d_{33} nonlinear coefficient in annealed proton-exchanged LiNbO_3 waveguides using reflected second-harmonic generation from angle-lapped samples.

The Yu N. Korkishko et al. article entitled "Reverse proton exchange for buried waveguides in LiNbO_3 ," J. Opt. Soc. Am. A, Vol. 15, No. 7, p.p. 1842 to 1842 (1998) describes a reverse proton-exchange (RPE) process performed in different $\text{H}_x\text{Li}_{1-x}\text{NbO}_3$ crystalline phases of proton-exchanged and annealed proton-exchanged LiNbO_3 waveguides.

The J. L. Jackel et al. article entitled "Reverse Exchange Method For Burying Proton Exchanged Waveguides," Electronics Letters, Vol. 27, No. 15, p.p. 1360 and 1361 (19 July 1991) describes formation of buried proton-exchanged LiNbO_3 waveguides. Following initial exchange and annealing steps which define the waveguides, a second exchange reintroduces lithium to lower the extraordinary refractive index at the surface.

The Ming-Hsin Chou (a co-inventor of the instant invention) dissertation entitled "Optical Frequency Mixers Using Three-Wave Mixing For Optical Fiber Communications" submitted to the Department of Applied Physics and the Committee on Graduate Studies of Stanford University in partial fulfillment of the requirements for the degree of Doctor of Philosophy (August 1999) describes the development of optical frequency (OF) mixers fabricated in periodically poled LiNbO_3 (PPLN) waveguides for optical fiber communications and other all-optical signal processing applications.

U.S. Patent No. 5,521,750 to Onoe et al. describes a process for forming proton-exchange layer and wavelength converting element.

U.S. Patent No. 4,948,407 to Bindell et al. describes a proton-exchange method of forming waveguides in LiNbO_3 .

U.S. Patent No. 5,734,494 to Xu et al. describes a wavelength conversion device and wavelength conversion method.

U.S. Patent No. 5,838,486 to Sonoda et al. describes an optical wavelength conversion element, a method of manufacturing the same, and an optical wavelength conversion module.

U.S. Patent No. 5,991,490 to Mizuuchi et al. describes an optical waveguide and optical wavelength conversion device.

U.S. Patent No. 5,872,884 to Mizuuchi et al. describes an optical waveguide conversion device.

U.S. Patent No. 6,002,515 to Mizuuchi et al. describes a method for producing a polarization inversion part, an optical wavelength conversion element using the same, and an optical waveguide.

U.S. Patent No. 5,943,465 to Kawaguchi et al. describes an optical waveguide element, an optical element, a method for producing an optical waveguide element and a method for producing periodic domain-inverted structure.

U.S. Patent No. 5,761,226 to Gupta describes frequency conversion laser devices.

U.S. Patent No. 5,652,674 to Mizuuchi et al. describes a method for manufacturing domain-inverted regions, optical wavelength conversion devices utilizing such domain-inverted regions and a method for fabricating such a device.

U.S. Patent No. 5,875,053 to Webjorn et al. describes periodic electric field poled crystal waveguides.

U.S. Patent No. 5,434,700 to Yoo describes an all-optical wavelength converter.

U.S. Patent No. 5,317,666 to Agostinelli et al. describes a waveguide nonlinear optical frequency converter with integral modulation and optimization means.

U.S. Patent No. 4,925,263 to Sanford et al. describes proton-exchanged waveguides for sum-frequency generation.

U.S. Patent No. 5,380,410 to Sawaki et al. describes a process for fabricating an optical device for generating a second harmonic optical beam.

U.S. Patent No. 5,249,191 to Sawaki et al. describes a waveguide type second-harmonic generation element and method of producing the same.

U.S. Patent No. 5,155,791 to Hsiung describes hybrid optical waveguides for phase-matched nonlinear wavelength conversion.

SUMMARY OF THE INVENTION

Accordingly, it is an object of one or more embodiments of the present invention to provide an improved method of forming waveguides.

It is another object of one or more embodiments of the present invention to provide an improved method to engineer the device geometry with preferred optical properties for performance optimization.

Other objects will appear hereinafter.

It has now been discovered that the above and other objects of the present invention may be accomplished in the following manner. Specifically, a ferroelectric crystal is provided. A vapor phase proton is diffused into the ferroelectric crystal by a vapor proton-exchange process to form a vapor proton-exchange (VPE) waveguide material structure having a step refractive index profile. The VPE waveguide material structure is treated with one or more processes selected from the group consisting of: a post thermal anneal process and an additional reverse proton-exchange process to complete fabrication of the waveguide, whereby the refractive index profile of the fabricated waveguide is smoothed as compared to the step refractive index profile of the VPE waveguide material structure. The method described in this invention will allow fabrication of high quality waveguides with preferred optical properties and also allow design of refractive index profile for device performance optimization. For example, one will

[illegible]

BRIEF DESCRIPTION OF THE DRAWINGS

The present invention will be more clearly understood from the following description taken in conjunction with the accompanying drawings in which like reference numerals designate similar or corresponding elements, regions and portions and in which:

Figs. 1 (a) through (g) are a series of graphs illustrating x-ray rocking curves for prior art samples 'a' through 'g' formed waveguide.

Fig. 2 is a table illustrating the refractive index change/refractive index jump for prior art samples "a" through "f" formed waveguides.

Fig. 3 is a graph illustrating index profiles for the prior art samples "a" through "f" formed waveguides of Fig. 2.

Figs. 4 to 7 schematically illustrate preferred embodiments of the present invention.

Figs. 8a through f schematically illustrate the resultant physical embodiments of the channel waveguides formed by the processes illustrated in Figs 4 to 7 as described herein.

Figs. 9a and 9b schematically illustrate another example applications of the present invention.

Figs. 10 a through g schematically illustrates modified processes described in this invention to form a multi-layer waveguide geometry.

Figs. 11a and 11b schematically represent physical embodiments of modified processes described in this invention to form a multi-layer waveguide geometry.

#0042570 "040502

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENT

As shown in Figs. 8a-f (with Fig. 8a a cross-sectional representation of Fig. 8b; Fig. 8c a cross-sectional representation of Fig. 8d; and Fig. 8e a cross-sectional representation of Fig. 8f), the processes described in this invention may be used to form high performance channel waveguides in the substrate with poled microstructures. Such type of devices has wide applications for nonlinear frequency conversion and optical frequency mixing.

Figs. 9a and 9b schematically illustrate other example applications of the present invention. Patterned electrodes at the sides of waveguides (Fig. 9a) and directly on top of waveguides (Fig. 9b) are shown as examples.

Figs. 10 a - g schematically illustrates the modified processes described in this invention (by combining the processes of the four embodiment processes illustrated in Figs. 4 through 7) to form a multi-layer waveguide geometry. Such a structure has application for dispersion shifting, dispersion flattening, or efficiency enhancement.

- Description of Figs. 10a through 10g:
 - a. Fig. 10a: VPE process is performed on substrate to form an initial index profile.

- b. Fig. 10b: Subsequent RPE process is performed to form a deep buried waveguide profile as a first sub-layer.
- c. Fig. 10c: Subsequent VPE process is performed to form another sub-layer of waveguide profile.
- d. Fig. 10d: Subsequent RPE process is performed to form another sub-layer of waveguide profile.
- e. Fig. 10e: Subsequent VPE process is performed to form another sub-layer of waveguide profile.
- f. Fig. 10f: Subsequent RPE process is performed to form another sub-layer of waveguide profile
- g. Fig. 10g: (Optional) post thermal annealing can be performed to form the final profile of multi-layer waveguide structure.

Basically, Figs. 10a through 10 g illustrate an example of combining the process of the four embodiment processes illustrated in Figs. 4 through 7. The example of Figs. 10a - g show the extension of processes illustrated in Figs. 4 through 7 by using a series of the processes, i.e. RPE/VPE/RPE/VPE...RPE/VPE, to form a more complex multi-layer waveguide.

Figs. 11a and 11b represent physical embodiments of waveguides fabricated by using a series of the processes illustrated in Figs. 4 through 7. Fig. 11a illustrates a waveguide 804 formed within a substrate 800 (formed of LiNbO_3 , for example) with an overlying channel waveguide mask 802 (formed of SiO_2 , for example). Fig. 11b illustrates another waveguide 904 formed within a substrate 900

(formed of LiNbO_3 , for example) with an overlying channel waveguide mask 902 (formed of SiO_2 , for example).

The processes of the present invention consist of fabricating waveguides using vapor phase proton-exchange (VPE) followed by a post-thermal annealing treatment and/or a reversed proton-exchange process in ferroelectric materials/crystals such as lithium niobate (LiNbO_3), lithium tantalate (LiTaO_3), KTiOPO_4 (KTP), KNbO_3 or KDP and their family such as $\text{MgO}:\text{LiNbO}_3$, $\text{ZnO}:\text{LiNbO}_3$, periodically poled KTP (PP-KTP) periodically poled lithium niobate (PP-LN) or periodically poled lithium tantalate (PP-LT) at different crystal orientations, i.e. X-cut, Y-cut or Z-cut. The more preferred ferroelectric materials/crystal is LiNbO_3 or LiTaO_3 and their family and the most preferred ferroelectric materials/crystal is LiNbO_3 and its family.

More specifically, the LiNbO_3 and their family include crystal at different formats such as congruent LiNbO_3 (CLN) and stoichiometric LiNbO_3 (SLN); above crystals with doping such as $\text{MgO}:\text{CLN}$, $\text{ZnO}:\text{CLN}$, $\text{MgO}:\text{SLN}$, $\text{ZnO}:\text{SLN}$; above crystals at different crystal orientations i.e. X-cut, Y-cut or Z-cut; and above crystals with periodic or aperiodic ferroelectric domain reversals in their crystal bodies.

Figs. 4 to 7 illustrate the one dimensional refractive indices in the depth direction of the preferred alternate embodiment waveguides of the present invention as the respective waveguides are formed.

As the preferred applications are used in the form of two dimensional channel waveguide structures, one should know that Figs. 4 to 7 only illustrate the cross-section in the depth direction of two dimensional channel waveguides. The actual two dimensional index profiles will depend on the width of waveguide channels, which are in general defined through the predefined waveguide channel mask before the processes described in this invention.

Those processes (as shown in Figs. 4 through 7) are compatible with each other as they offer different design and process flexibility to each other. The RA-VPE (VPE + annealing + RPE) (as shown in Fig. 5) and AR-VPE (VPE + RPE + Annealing) (as shown in Fig. 7) are the most generic and more preferred methods as they offers maximum degree of freedoms in process for device deign and optimization.

However, A-VPE (VPE + annealing) (as shown in Fig. 4) offers simplicity due to reduce process step and R-VPE (VPE+ RPE) (as shown in Fig. 6) offers very high index step with buried structures. [One may also view the Fig. 4 A-VPE and Fig. 6 R-VPE as the degenerate/simplified versions of the Fig. 5 RA-VPE and the Fig. 7 AR-VPE, respectively.] Because it is not always possible to achieve a particular preferred index profile by a single approach, the above combinations offer a complete method to fabricate high-quality waveguide and simultaneously provide design flexibility.

Step Common to Each Embodiment

In each embodiment (Figs. 4 through 7), the vapor phase proton is first diffused into the ferroelectric crystal material such as LiNbO_3 (lithium niobate) (step A) by a vapor proton-exchange (VPE) process to form a high-quality waveguide material structure (VPE) having a step refractive index profile as shown in Fig. 4A, Fig. 5A, Fig. 6A and Fig. 7A.

This VPE process may be performed in: 1) pure acid vapor such as, for example, benzoic acid, stearic acid or pyrophosphoric acid; 2) buffering acid vapor such as, for example, benzoic acid buffered with different lithium benzoate concentrations, or stearic acid buffered with different lithium stearate concentrations; to adjust the initial proton concentration and crystal phase before post annealing and/or reversed proton exchange for the specific embodiments of Figs. 4 to 7.

The adjusted proton concentration is preferably from about 10^{21} to 2×10^{22} atoms/cm³ and is more preferably from about 2×10^{21} to 2×10^{22} atoms/cm³. The proton source is preferably benzoic acid or another chemical acid vapor containing hydrogen such as stearic acid or pyrophosphoric acid and is more preferably benzoic acid and its family.

The thermal anneal process of the First (Fig. 4), Second (Fig. 5) and Fourth (Fig. 7) Embodiments are identical.

The additional reverse proton-exchange processes of the Second (Fig. 5), Third (Fig. 6) and Fourth (Fig. 7) Embodiments also identical.

First Embodiment: Formation of A-VPE Waveguide - Fig. 4

As shown in Fig. 4 (the first embodiment) the waveguide material structure having a step refractive index profile as illustrated in Fig. 4A is post-thermally annealed to diffuse the proton formed by the VPE process into the LiNbO_3 to produce an A-VPE waveguide having a smoother refractive index profile as illustrated in Fig. 4B.

The first embodiment post-thermal anneal is conducted at the following conditions:

temperature: preferably from about 250 to 400°C and more

preferably from about 300 to 360°C; and

time: preferably from about 1 to 72 hours and more preferably from about 1 to 36 hours. with the optimized processing temperature and time will depend on the optimized design for specific applications.

Figs. 8a and 8b illustrate a cross-sectional and perspective views, respectively, of the physical embodiment of the A-VPE channel waveguide of Fig. 4 showing substrate 100 (e.g. LiNbO_3), channel waveguide mask 102 (e.g. SiO_2) and

A-VPE channel waveguide 104. Substrate 100 has poled microstructures, for example periodically poled LiNbO₃ as shown.

Second Embodiment: Formation of RA-VPE Waveguide - Fig. 5

As shown in Fig. 5 (the second embodiment) the waveguide material structure having a step refractive index profile as illustrated in Fig. 5A is post-thermally annealed to diffuse the proton formed by the VPE process into the LiNbO₃ to produce a waveguide having a smoother refractive index profile as illustrated in Fig. 5B.

The second embodiment post-thermal anneal is conducted at the same conditions as the A-VPE (Fig. 4) post-thermal anneal process.

Next, the waveguide is further optimized by an additional reverse proton-exchange process to form a buried waveguide and to shape the waveguide mode profile as illustrated in Fig. 5C.

The second embodiment additional reverse proton-exchange process is conducted at the following conditions:

Reverse proton chemical source is preferably performed in a mixture of LiNO₃-KNO₃-NaNO₃ by adjusting the composition ratio of the chemical mixtures, preferably with an LiNO₃ concentration of from about 30 to 45 mol. % and more preferably from about 35 to 40 mol. %;

preferably with a KNO_3 concentration of from about 30 to 60 mol. % and more preferably from about 40 to 50 mol. %; preferably with NaNO_3 concentration of from about 10 to 30 mol. % and more preferably from about 15 to 25 mol. %;

temperature: preferably from about 200 to 400°C and more preferably from about 250 to 350°C; and

time: preferably from about 1 to 72 hours and more preferably from about 1 to 36 hours with the optimized processing temperature and time depending upon the optimized waveguide design for specific applications.

Figs. 8e and 8f illustrate a cross-sectional and perspective views, respectively, of the physical embodiment of the RA-VPE channel waveguide of Fig. 5 showing substrate 300 (e.g. LiNbO_3), channel waveguide mask 302 (e.g. SiO_2) and RA-VPE channel waveguide 304. Substrate 300 has poled microstructures, for example periodically poled LiNbO_3 as shown.

Third Embodiment: Formation of R-VPE Waveguide - Fig. 6

As shown in Fig. 6 (the third embodiment) the waveguide material structure having a step refractive index profile as illustrated in Fig. 6A is subjected to an additional reverse proton-exchange process to form a buried waveguide and to shape the waveguide mode profile as illustrated in Fig. 6B.

The third embodiment additional reverse proton-exchange process is conducted at the same conditions as the second embodiment RA-VPE (Fig. 5)

reverse proton-exchange process with the optimized processing temperature and time depending upon the optimized waveguide design for specific applications.

Figs. 8c and 8d illustrate a cross-sectional and perspective views, respectively, of the physical embodiment of the R-VPE channel waveguide of Fig. 6 showing substrate 200 (e.g. LiNbO_3), channel waveguide mask 202 (e.g. SiO_2) and R-VPE channel waveguide 204. Substrate 200 has poled microstructures, for example periodically poled LiNbO_3 as shown.

Fourth Embodiment: Formation of AR-VPE Waveguide - Fig. 7

As shown in Fig. 7 (the fourth embodiment) the waveguide material structure having a step refractive index profile as illustrated in Fig. 7A is subjected to an additional reverse proton-exchange process to form a buried waveguide and to shape the waveguide mode profile as illustrated in Fig. 7B.

The fourth embodiment additional reverse proton-exchange process is conducted at the same conditions as the second RA-VPE (Fig. 5) and third R-VPE (Fig. 6) reverse proton-exchange processes with the optimized processing temperature and time depending upon the optimized waveguide design for specific applications.

Next, the waveguide is further optimized by a post-thermal anneal to diffuse the proton formed by the VPE process into the LiNbO_3 to produce an AR-VPE waveguide having a smoother refractive index profile as illustrated in Fig. 5C.

The fourth embodiment post-thermal anneal is conducted at the same conditions as the first embodiment A-VPE (Fig. 4) and second embodiment RA-VPE (Fig. 5) post thermal anneal processes with optimized processing temperature and time will depending upon the optimized waveguide design for specific applications.

Figs. 8e and 8f illustrate a cross-sectional and perspective views, respectively, of the physical embodiment of the AR-VPE channel waveguide of Fig. 7 showing substrate 300 (e.g. LiNbO_3), channel waveguide mask 302 (e.g. SiO_2) and RA-VPE channel waveguide 304. Substrate 300 has poled microstructures, for example periodically poled LiNbO_3 as shown. (It is noted that Figs. 8e and 8f illustrates both the AR-VPE and RA-VPE channel waveguides of Figs. 5 and 7.)

Such A-VPE (Fig. 4), RA-VPE (Fig. 5), R-VPE (Fig. 6) and AR-VPE (Fig. 7) processes not only allow the production of high quality waveguides, but also provides a full degree of design flexibility for device optimization. For example, a high quality, smoother refractive index profile can be formed by A-VPE, which provides an extra degree of freedom to adjust the high-quality, high step index profile waveguides as produced by VPE process. A high quality, buried waveguide can be obtained by R-VPE process, which allows maintain a high index step profile produced by VPE process and also form a more symmetric structure in depth

direction. A high quality, symmetric and buried waveguide with smoother index profile can be obtained by RA-VPE and/or AR-VPE processes. RA-VPE process allows independent adjustment of VPE profile first through thermal annealing and then performs reversed proton exchange process to form a desired structure. While AR-VPE process allows simultaneously tailoring waveguide profile and then generates a more symmetric waveguide structure.

Thus above process allows flexible waveguide profile optimization for a wide variety of applications. Example applications are nonlinear frequency conversion such as blue light generation and telecommunication optical frequency mixers in high-quality, symmetric buried waveguide fabricated in ferroelectric nonlinear materials. The device optimization requires maximizing the integral overlapping of optical mode profiles at several different wavelengths and nonlinear materials. In addition, it also requires operating at preferred crystal phase to reduce the propagation loss. The fabrication process described in this invention will allow achieving the low loss and high-nonlinearity devices, and also simultaneously allows designing waveguide geometry to maximize the overall device efficiency by adjusting the optical mode profiles through the flexible fabrication steps.

Furthermore, mass production with a full wafer process could also be carried out using the embodiments of the present invention. The processes of the present invention can also be used for efficiency and fabrication optimization, and to produce a particular design such as noncritical structure design.

The embodiments of the present invention may be used in the following process applications:

- 1) quasi-phase matching waveguides and nonlinear guided wave applications such as: second harmonic generation; sum frequency generator difference frequency generation; wavelength converters; dispersion compensation elements; nonlinear compensation elements; optical parametric frequency amplification and generation; cascaded nonlinear frequency conversion; light source for laser display, laser scanner, laser printing, laser spectroscopic, sensing and detection; optical frequency mixers for optical fiber communication and optical signal processing etc.;
- 2) electro-optics applications and their optimizations such as electro-optics amplitude, phase modulators or high-speed modulators (see Figs. 9a and 9b);
- 3) acoustic optics applications and optimization; and
- 4) integrated optics and waveguide coupling optimization.

Advantages of the Present Invention

The advantages of one or more embodiments of the present invention include:

1. high quality waveguide and process optimization: producing high index, symmetric, buried waveguides with lower propagation loss but also preserving material optical properties, such as nonlinear coefficients and electro-optic coefficients;

2. design flexibility for application optimization: the process steps offer high degree of freedoms for design optimization to a variety of applications;

3. only a few key process steps (i.e. VPE, RPE, Thermal annealing) are needed to develop and optimize. With a combination of above optimized process steps, a highly degree of freedom in fabrication process and design can be achieved. Thus, a sophisticated fabrication and design method can be offered only through three key process steps;

4. ease of further optimization and produce novel devices: Based on those three key optimized process steps, additional process and design combination can be easily developed. Examples are implementation of several sequential R-VPE, RA-VPE or AR-VPE processes to generate multi-layer waveguide structures for specific applications, such as fabrication of dispersion shifting waveguides, dispersion flattened waveguides efficiency enhancement for quasi-phase matching waveguides, nonlinear guided wave applications and integrated optics and waveguide optimization applications; an analogy to this type of design and devices is those used in optical fiber design and fabrication of dispersion shifting fiber or dispersion flattened fiber; and

5. two dimensional noncritical waveguide structures. As the method offers design and process flexibility, it can be used to generate a waveguide designs with optimized waveguide width and depth profiles simultaneously. Waveguide with such a design will have very stable properties and have a very high process tolerance, i.e. less sensitive to process condition, such as channel width variation, process temperature uniformity, and temperature stability etc.

23 1900 1901 1902 1903 1904 1905 1906 1907 1908 1909 1910 1911 1912 1913 1914 1915 1916 1917 1918 1919 1920 1921 1922 1923 1924 1925 1926 1927 1928 1929 1930 1931 1932 1933 1934 1935 1936 1937 1938 1939 1940 1941 1942 1943 1944 1945 1946 1947 1948 1949 1950 1951 1952 1953 1954 1955 1956 1957 1958 1959 1960 1961 1962 1963 1964 1965 1966 1967 1968 1969 1970 1971 1972 1973 1974 1975 1976 1977 1978 1979 1980 1981 1982 1983 1984 1985 1986 1987 1988 1989 1990 1991 1992 1993 1994 1995 1996 1997 1998 1999 2000 2001 2002 2003 2004 2005 2006 2007 2008 2009 2010 2011 2012 2013 2014 2015 2016 2017 2018 2019 2020 2021 2022 2023 2024 2025 2026 2027 2028 2029 2030 2031 2032 2033 2034 2035 2036 2037 2038 2039 2040 2041 2042 2043 2044 2045 2046 2047 2048 2049 2050 2051 2052 2053 2054 2055 2056 2057 2058 2059 2060 2061 2062 2063 2064 2065 2066 2067 2068 2069 2070 2071 2072 2073 2074 2075 2076 2077 2078 2079 2080 2081 2082 2083 2084 2085 2086 2087 2088 2089 2090 2091 2092 2093 2094 2095 2096 2097 2098 2099 2100 2101 2102 2103 2104 2105 2106 2107 2108 2109 2110 2111 2112 2113 2114 2115 2116 2117 2118 2119 2120 2121 2122 2123 2124 2125 2126 2127 2128 2129 2130 2131 2132 2133 2134 2135 2136 2137 2138 2139 2140 2141 2142 2143 2144 2145 2146 2147 2148 2149 2150 2151 2152 2153 2154 2155 2156 2157 2158 2159 2160 2161 2162 2163 2164 2165 2166 2167 2168 2169 2170 2171 2172 2173 2174 2175 2176 2177 2178 2179 2180 2181 2182 2183 2184 2185 2186 2187 2188 2189 2190 2191 2192 2193 2194 2195 2196 2197 2198 2199 2200 2201 2202 2203 2204 2205 2206 2207 2208 2209 2210 2211 2212 2213 2214 2215 2216 2217 2218 2219 2220 2221 2222 2223 2224 2225 2226 2227 2228 2229 2230 2231 2232 2233 2234 2235 2236 2237 2238 2239 2240 2241 2242 2243 2244 2245 2246 2247 2248 2249 2250 2251 2252 2253 2254 2255 2256 2257 2258 2259 2260 2261 2262 2263 2264 2265 2266 2267 2268 2269 2270 2271 2272 2273 2274 2275 2276 2277 2278 2279 2280 2281 2282 2283 2284 2285 2286 2287 2288 2289 2290 2291 2292 2293 2294 2295 2296 2297 2298 2299 2300 2301 2302 2303 2304 2305 2306 2307 2308 2309 2310 2311 2312 2313 2314 2315 2316 2317 2318 2319 2320 2321 2322 2323 2324 2325 2326 2327 2328 2329 2330 2331 2332 2333 2334 2335 2336 2337 2338 2339 2340 2341 2342 2343 2344 2345 2346 2347 2348 2349 2350 2351 2352 2353 2354 2355 2356 2357 2358 2359 2360 2361 2362 2363 2364 2365 2366 2367 2368 2369 2370 2371 2372 2373 2374 2375 2376 2377 2378 2379 2380 2381 2382 2383 2384 2385 2386 2387 2388 2389 2390 2391 2392 2393 2394 2395 2396 2397 2398 2399 2400 2401 2402 2403 2404 2405 2406 2407 2408 2409 2410 2411 2412 2413 2414 2415 2416 2417 2418 2419 2420 2421 2422 2423 2424 2425 2426 2427 2428 2429 2430 2431 2432 2433 2434 2435 2436 2437 2438 2439 2440 2441 2442 2443 2444 2445 2446 2447 2448 2449 2450 2451 2452 2453 2454 2455 2456 2457 2458 2459 2460 2461 2462 2463 2464 2465 2466 2467 2468 2469 2470 2471 2472 2473 2474 2475 2476 2477 2478 2479 2480 2481 2482 2483 2484 2485 2486 2487 2488 2489 2490 2491 2492 2493 2494 2495 2496 2497 2498 2499 2500 2501 2502 2503 2504 2505 2506 2507 2508 2509 2510 2511 2512 2513 2514 2515 2516 2517 2518 2519 2520 2521 2522 2523 2524 2525 2526 2527 2528 2529 2530 2531 2532 2533 2534 2535 2536 2537 2538 2539 2540 2541 2542 2543 2544 2545 2546 2547 2548 2549 2550 2551 2552 2553 2554 2555 2556 2557 2558 2559 2560 2561 2562 2563 2564 2565 2566 2567 2568 2569 2570 2571 2572 2573 2574 2575 2576 2577 2578 2579 2580 2581 2582 2583 2584 2585 2586 2587 2588 2589 2590 2591 2592 2593 2594 2595 2596 2597 2598 2599 2600 2601 2602 2603 2604 2605 2606 2607 2608 2609 2610 2611 2612 2613 2614 2615 2616 2617 2618 2619 2620 2621 2622 2623 2624 2625 2626 2627 2628 2629 2630 2631 2632 2633 2634 2635 2636 2637 2638 2639 2640 2641 2642 2643 2644 2645 2646 2647 2648 2649 2650 2651 2652 2653 2654 2655 2656 2657 2658 2659 2660 2661 2662 2663 2664 2665 2666 2667 2668 2669 2670 2671 2672 2673 2674 2675 2676 2677 2678 2679 2680 2681 2682 2683 2684 2685 2686 2687 2688 2689 2690 2691 2692 2693 2694 2695 2696 2697 2698 2699 2700 2701 2702 2703 2704 2705 2706 2707 2708 2709 2710 2711 2712 2713 2714 2715 2716 271